

# BETA



isoTek®  
SMART Power

A 2U (89mm) high rack width component, offering full system control of connected electronics through RS232, LAN, Bluetooth and over WiFi with a Smartphone App. Beta features six UK (BS 1363), European Schuko or American 3-pin output sockets along with RS232 via traditional and USB ports, LAN Ethernet port for WiFi control and antenna supporting Bluetooth. Input power is via standard IEC C15/16 connection. Beta also reduces Differential and Common Mode mains noise. Each output socket is independently cleaned avoiding mains noise cross contamination between connected electronics. Beta protects connected equipment up to 54000A.

- Name each outlet with connected electronics
- Turn on / off each outlet independently
- Remote reboot and sequential start-up
- Programmable delay times between each outlet upon start-up
- Control each outlet independently with date and time start-up
- Combine two or more units into named groups
- Manage power usage and overview power consumption
- Protection against power surges and voltage spikes
- Power cleaning network and RFI reduction of 45dB
- Control through RS232, LAN, Bluetooth and over WiFi with a Smartphone App

## SPECIFICATIONS

Output sockets:	6
Outlet socket style:	UK (BS 1363), EU Schuko, US 3-pin
Mains voltage:	100-240V / 50-60Hz
Amperage:	10A
Total (continuous) power:	2300W (230V) / 1150W (115V)
Protection rating:	54000A
Dimensions (mm):	448 x 305 x 89 (W x D x H)

# Isotek<sup>®</sup>

---

## SMART Power

© 2017 Audio Power Systems GmbH. All rights reserved.

Unauthorised copy or reproduction of any part of this booklet is prohibited and subject to prosecution.

Information contained in this brochure is correct at the time of printing, product improvements will take place from time to time.

